



Updating Firmware

Procedure and technical reference guide

Room Booking Display Panels
Room Booking Display Media Players

METHOD ONE: Direct update via on-prem network

Notes

- You can download the latest firmware updater program from [Downloads - Concierge Displays](#).
- Windows support only
- Unzip downloaded file on folder and run **ConciergePortableUpdater.exe**.
- Can update multiple panels at a time.
- All firmware versions supported

Network firewall considerations

The program requires access to URLs below to download necessary files. Ensure network firewall rules allow the following:

Preparation


- <https://dl.google.com/android/repository/>
 - Google Android platform-tools package (6 MB) is downloaded (*)
- <https://s3.amazonaws.com/download.us.iadea.com/support/firmware>
- <https://license.conciergedisplays.com.au/serve>
 - This is only required if panels are factory reset

During update

- TCP ports 8086 (HTTP), 8080 (HTTP) & 5555 (raw, opens after authorisation, closes on completion)

Anti-virus considerations

Windows Defender (or other anti-virus programs) may pop up an alert when executing the program. Please click **More info** and click **Run anyway**.



(*) Ensure the executable adb.exe is not prohibited from executing.


Download locations

C:\Users**user-name**\AppData\Local\Temp\

Screenshots

After executing the program

1. Console window: detailed realtime operation logging
2. UI window: you can add IP address of panels and start updating.
3. A list of IP addresses can be added here
4. Click “Add...” to append to target list
5. Click “Start” to commence firmware update of one or more panels



After starting update

```
C:\tmp\conciierge-fwupdate-v3.31-fw1661\ConciiergePortableUpdater.exe
--noGUI          Do not show GUI; use command-line args

where:
  IP_ADDRESS      The IP address(es) of the panels to update
  PASSWORD        The panel's admin password (if "admin" is not used)

NOTE: flag names are not case-sensitive
10:05:53.39      (checking dependencies...)
10:05:53.39 INFO  At least one dependency needs to be downloaded...
10:05:53.64 [.download]    Downloading platform-tools_r28.0.2-windows.zip, 10 MB...
.....
10:05:55.73      1 IP address specified
10:05:55.73 WARN  This tool may alter the installed revision of Conciierge software & firmware
10:05:55.73 WARN  Press Ctrl-C within the next 5 seconds to abort...
.....
10:06:15.30      [10.78.0.168]    REST API supports to update APK
10:06:15.36      [10.78.0.168]    REST API supports to update PKG
10:06:15.36      [10.78.0.168]    Trying to use REST API
10:06:15.38      [10.78.0.168]    Connecting and Authorizing...
10:06:15.39 SUCCESS [10.78.0.168]    Authorized!
10:06:17.41 SUCCESS [10.78.0.168]    ADAPI ready!
10:06:17.66      [10.78.0.168]    Model is XDS-1078; base firmware version is 2.2.8
10:06:18.13      [10.78.0.168]    Panel Firmware Version: 1.2.1661-perpetual-iadea1
10:06:23.16      [10.78.0.168]    Pushing Player / Panel update...
10:06:23.21      [10.78.0.168]    [Solutions] 'conciierge' found
10:06:25.14      [10.78.0.168]    File uploaded [C:\Users\ [redacted] \AppData\Local\Temp\ConciiergeFactoryImageUpdater.1661
t-perpetual_fw][6BEA3340D5FC9E37E2FE30767B5E26]
10:06:25.19      [10.78.0.168]    app/solutions/update done
10:06:28.26 SUCCESS [10.78.0.168]    Conciierge Player / Panel installed!
10:06:28.26      [10.78.0.168]    Waiting for reboot...
.....10:07:37.05      [10.78.0.168]    Tidied up
10:07:37.05 SUCCESS [10.78.0.168]    Update complete!
10:07:37.08      [10.78.0.168]    File deleted: 6BEA3340D5FC9E37E2FE30767B5E26
10:07:37.09      Progress: completed: 1, busy: 0, failures: 0
10:07:37.10 SUCCESS ALL LISTED TARGETS WERE PROCESSED SUCCESSFULLY! 10.78.0.168
Press Enter to finish / close Window
```

METHOD TWO: Device self update via Internet

Notes

- Only available since **fw1619** (November 2021)
- No need to download any additional programs.
- Firmware updates support core application (apk) and hardware platform (pkg) updates
- It is recommended PKG is done first, then APK.

Network firewall considerations

The panel will get access to URLs below to gather information and download necessary files. Please make sure they are allowed on firewall policies.

- <https://manage.conciergedisplays.co/serve/firmware>
- <https://s3.amazonaws.com/download.us.iadea.com/support/firmware>
- <https://conciierge-firmware.s3.ap-southeast-4.amazonaws.com>

Anti-virus considerations

N/A

Download locations

All downloaded files will be saved on local storage of the panel. They will be deleted after update.

Screenshots

Before starting update (on Configuration tab of admin page)

1. Tick **Advanced** and click **Technical** menu.
2. Input one of the following.
 - a. <https://manage.conciergedisplays.co/serve/firmware?apk=latest>
 - b. <https://manage.conciergedisplays.co/serve/firmware?pkg=latest>
 - c. In some cases, you can specify a specific version string like “**v1.00.999**” **instead of “latest”**.
3. Click Save to execute the update.

The screenshot shows the 'Technical' configuration page. At the top, there is a blue header with the word 'Technical' and a dropdown arrow. Below the header, there are several sections: 'Persistence period (minutes)' with an empty text input field; 'Skip splash screen' with an unchecked checkbox and the label 'Yes'; 'Firmware update' with a text input field containing '(2)'; a paragraph of explanatory text about over-the-air updates; a bulleted list with two items: 'For update (apk) : 'latest' or 'https://UPDATE-SERVER/serve/firmware?apk=latest'' and 'For firmware (pkg) : 'https://UPDATE-SERVER/serve/firmware?pkg=latest''; and 'Config save token (RESERVED FOR FUTURE USE)' with an empty text input field. At the bottom, there is a row of buttons: a green 'Save' button with a red '(3)' next to it, a white 'Advanced' checkbox with a checked mark and a red '(1)' next to it, and four red buttons: 'Import bulk config', 'Clear Authentication', 'Reset config', and 'Reboot'.

After update finished (on Status tab of admin page)

Concierge_AutoUpdate_Update 0 ▾

Category: Concierge_AutoUpdate_Update

Last occurrence: 18 days ago (04/21/2023)

Commentary at the time: Update completed

Lifetime count: 3

Concierge_AutoUpdate_Download 0 ▾

Category: Concierge_AutoUpdate_Download

Last occurrence: 18 days ago (04/21/2023)

Commentary at the time: Download completed. A new binary file saved: 9958531 bytes

Lifetime count: 2

Concierge_AutoUpdate_Request 0 ▾

Category: Concierge_AutoUpdate_Request

Last occurrence: 18 days ago (04/21/2023)


Commentary at the time: Metadata received: URL[...], fileName[...], versionName[1.2.1661-perpetual-idea1]

Lifetime count: 3


METHOD TWO BUT USING BULK CONFIG SHEET

You can update panels remotely using [Companion site](#).

1. Log in to [Companion site](#) and go to **Storage & Bulk Config**.



2. Click **Firmware Updates** and save the csv file on local storage.



3. Open .csv file with text editor or your own spreadsheet software (Excel or Google Sheets, for example)
 - a. **Keep rows for panels which should be targeted**
 - b. Default version string of APK is **“latest”**. In some cases, you can specify a specific version string like **“v1.00.999”** instead of **“latest”**.

```
match (id),advanced.firmwareUpdateAddress  
YOUR-PANEL-ID-00,https://manage.conciergedisplays.co/serve/firmware?apk=latest  
YOUR-PANEL-ID-01,https://manage.conciergedisplays.co/serve/firmware?apk=latest  
YOUR-PANEL-ID-02,https://manage.conciergedisplays.co/serve/firmware?apk=latest  
YOUR-PANEL-ID-03,https://manage.conciergedisplays.co/serve/firmware?apk=latest
```

4. Rename .csv file to **bulk_config.csv**.
5. Upload **bulk_config.csv** on [Companion site](#) (please back up an existing bulk_config.csv if necessary)

(1)


Drag & drop file here, or click to select file.

File Name

UPLOAD

File Url

Existing files

Created	File name
2023-04-20 12:56:44	bulk_config.csv  (2)

6. After their 15 min check-in period, the panels should commence the update